

Características Bluetti AC200P

Specifications

Info	AC200	AC200P
Capacity	1700Wh/2000W (Surge 4800W)	2000Wh/2000W (Surge 4800W)
Cycle Life	2500+cycle	3500+cycle
Cell Chemistry	LG Lithium	LifePo4
Warranty	2 Years	2 Years
Color	Black	Black
Net Weight	60.6lbs	60.6lbs
Dimension	16.5*11*15.2inch	16.5*11*15.2inch
Operating Temperature	0-40°C/10%-90%	0-40°C/10%-90%
Shelf-Life	Charge Every 3-6 Months	Charge Every 3-6 Months
Charging Method		
Five flexible charging methods: AC/Solar/Car/Generator/Lead Acid Battery		
AC Adapter (Included): 400W (About 4.5 hours)		
Car Charger (Included): 12V/ 24V (About 14 hours/12V About 7 hours/24V)		
Solar Panel (Not Included): 35-150v/ Max.700W,Max12A (About 4-7 hours)		
Generator: gasoline, Propane Or Diesel (About 4.5 hours /Gas-Fired Generator)		
Lead Acid Battery (Max 8.2A)		
Output Ports		
2* AC 220-240V output (max. 2000W, pure sine wave)		
1* DC12V/25A		
1* DC12V/10A		
2* DC 12V/3A		
4* 5V/3A USB-A		
1* PD 60W USB-C Faster Charge (5V/3A, 9V/3A, 12V/3A,15V/3A, 20V/3A)		
2* Wireless Charging (Single Output Max 15W)		

Note: Support PV+Adapter Charge Simultaneously. Max 1200W,1.7-2.7Hrs To Full Recharge It.